

GUB231

## 2-Port USB 2.0 Automatic Printer Switch



IOGEAR's USB 2.0 Automatic Printer Switch allows two PCs and/or Macs to share one printer or multi-function printer. Simply submit a print job and the printer automatically\* switches to the preferred computer. The switch also enables two computers to easily share one external hard drive, scanner, or any USB device. No more plugging and unplugging between computers.


\* Automatic switch function is software based and only available with USB printer or the printer function of a multi-function printer. For connecting and using other types of USB devices, you can switch by using the push-button on the USB switch or with the included software.

- Automatically\* switch from one computer to another when connecting to a USB printer or multi-function printer
- Easily share a USB 2.0 device between PC and Mac without a network setup
- Simply press a button to switch a USB device between computers - No software installation required
- Active-port LED lights indicate which computer has access to the USB device
- Switch-lock function prevents other users from switching the USB device and ensures data access consistency
- USB 2.0 support with data transfer rate up to 480Mbps and USB 1.1 backward compatible
- No external power supply needed



**How does it work?**

- Connect your USB device (i.e. printer, external hard drive, or scanner) to the USB-A connector
- Connect your computers (PC or Mac) to the USB-B connector
- Simply push the button to swap or enable automatic\* switch between two computers

**Requirements****For PC Users**

- Windows 8.1, Windows 10, Windows 11
- Available USB port
- Chrome Book
- Linux®, Unix and other USB supported systems\*

\*Additional drivers and support may be needed

**Package Contents**

- 1 x USB 2.0 Auto Switch
- 1 x 6 ft. USB A-B Cable
- 1 x User Manual
- 1 x Registration / Warranty Card

**For MAC Users**

- macOS 12 and above
- Available USB port

**Specifications**

Function	GUB231	Dimensions	GUB231
<b>Computer Connections</b>		<b>POP Information</b>	
Direct	USB Type B to Type A	10" Peg Hook	4
<b>Connectors</b>		6" Peg Hook	3
Console	1 x USB Type A	<b>Unit Dimensions</b>	
Device Side	2 x USB Type B	Height	2.75"
<b>Environment</b>		Depth	1"
Humidity	0-80% RH	Width	2.5"
Operation Temperature	41 to 104 degree Fahrenheit	<b>Unit Package Dimensions</b>	
Storage Temperature	-4 to 140 degree Fahrenheit	Height	7.25"
<b>LEDs</b>		Width	6"
Port Status	Green - Online / Orange - Locked	Depth	2.25"
Host Status	Orange - Online	<b>Master Carton</b>	
<b>Operating System Support</b>		Height	7"
Windows XP and above; Mac: 10.4.5, 10.5 and above		Width	8"
<b>Power Consumption</b>		Depth	15"
DC 5V, 2.5W		Master Carton Qty.	6
<b>Power Supply</b>		<b>Weight</b>	
USB Bus powered		Master Carton Wt.	4.5 lb.
		Unit Pack Wt.	0.65 lb.
		Unit Wt.	0.1 lb.