

GUS432CA1KIT

## 2x4 USB 3.0 Peripheral Sharing Switch with USB-C Adapter



- Share 4 separate USB 3.0 devices between 2 computers
- Connect a USB-C PC or Mac via the included USB-A to USB-C adapter cable.
- Easy push-button switching between computers
- Supports data transfer rates of up to 5 Gbps
- LED indicates which computer is active

### Share USB 3.0 Peripherals With Two Computers

IOGEAR's 4x2 USB 3.0 Peripheral Sharing Switch is a convenient way to share four (4) USB devices between two (2) USB-A or USB-C computers. Share a keyboard, mouse, printer, portable hard drive and more with simple push-button switching.

### Connect USB-C Computers to Existing Devices

Share your existing USB-A peripheral devices with the newest USB-C-enabled laptop or tablet with the included USB-A to USB-C adapter cable.

### Save Space and Expense

The Peripheral Sharing Switch is perfect for small office, and home office users since it not only saves users from purchasing duplicate peripherals, it also creates a space saving, productive work environment.

- Share 4 separate USB 3.0 devices between 2 computers
- Connect a USB-C PC or Mac via the included USB-A to USB-C adapter cable.
- Easy push-button switching between computers
- Supports data transfer rates of up to 5 Gbps
- LED indicates which computer is active
- Features over-current protection
- Connect or remove computers via hot-plugging without powering down
- Connect optional Micro USB cable to support additional power (up to 2.5W via USB 2.0 Port, up to 4.5W via USB 3.0 Port)





### Requirements

### Package Contents

- For PC Users
  - Windows XP, Windows Vista, Windows 7, Windows 8/8.1, 10
  - Available USB 3.0 port
  - Available USB-C port
  - Chrome Book
  - Linux®, Unix and other USB supported systems<sup>1</sup>
  - 
  - For MAC Users
  - Mac 8.6 or greater. Requires OS X for USB 3.0 support
  - Available USB 3.0 port
  - Available USB-C port
- 1 x 2x4 USB 3.0 Peripheral Sharing Switch
  - 1 x Quick Start Guide
  - 1 x Warranty Card
  - 1x USB-C to A Adapter (G2LU3CAF10-SIL)

<sup>1</sup>Additional drivers and support may be needed

## Specifications

Function	GUS432CA1KIT
<b>Computer Connections</b>	
Direct	2
<b>Port Selection</b>	
Remote control selector button	
<b>LEDs</b>	
Port Status	White
<b>Switches</b>	
Port Selection	Remote Console Selector Button x 1
<b>Connectors</b>	
Computer Side	USB 3.0 Type B x 2
USB	USB 3.0 Type A x 4
Power	USB Type Micro B (optional)
<b>Operating Temperature</b>	
	32 ~ 104F (0 ~ 40C)
<b>Storage Temperature</b>	
	-4 ~ 140F (-20 ~ 60C)
<b>Humidity</b>	
	0~80%
<b>Cable Length</b>	
	54" (137.16cm)
<b>Cable Type</b>	
	USB 3.0 Type B to A x 4
<b>Power Consumption</b>	
	DC 5V, 1.43W

Dimensions	GUS432CA1KIT
<b>Unit Dimensions</b>	
Height	3.75" (9.53cm)
Depth	1.06" (2.69cm)
Length	3.75" (9.53cm)
<b>Unit Package Dimensions</b>	
Width	6.5" (16.51cm)
Height	9.25" (23.50cm)
Depth	2.875" (7.30cm)
<b>Master Carton</b>	
Width	10" (254mm)
Height	7" (177.8mm)
Depth	4" (101.6mm)
Master Carton Qty.	1
<b>Weight</b>	
Master Carton Wt.	1.2lb (.54kg)
Unit Pack Wt.	0.95 lb (0.42 kg)
Unit Wt.	0.27lb (0.124kg)